

# AMT-12/24-R Multitone Electronic Appliance (red)

www.boschsecurity.com



**BOSCH**  
Invented for life



- ▶ Three separate supervised prioritized inputs activate three electrically-isolated signals
- ▶ Power taps for high dBA and standard dBA
- ▶ Low current draw with low temperature compensation
- ▶ Selectable voltage input (12 VDC or 24 VDC)
- ▶ Voltage inputs polarized for use with reverse polarity supervision systems

The Wheelock AMT-12/24-R Multitone Electronic Appliances provide eight groups of three distinct self-prioritized sound outputs from separate electrically isolated input terminals. Priority 1 overrides all other commands upon activation. Choose from high dBA or standard dBA sound output. These appliances operate on 12 VDC or 24 VDC, filtered or FWR. They are listed for indoor or outdoor use with the specified back boxes. Use these appliances in suppression releasing systems, combination security and emergency evacuation systems, and high risk installations.

## Functions

### Self-Prioritized Tones

Choose any of the following eight groups of self-prioritized tones:

### Self-Prioritizing Groups

	Priority 1	Priority 2	Priority 3
1	Horn	Bell	Siren
2	Code 3 Horn*	Siren	Vibrating Chime

3	Slow Whoop	March Time Horn	Hi-Lo
4	March Time Horn	Hi-Lo	Vibrating Chime
5	Code 3 Horn*	Bell	Siren
6	Siren	Horn	Vibrating Chime
7	Bell	March Time Horn	Siren
8	Code 3 Tone*	Hi-Lo	Siren

\* The Code 3 Horn and Code 3 Tone, when set for high dBA, incorporate the temporal pattern specified by ANSI and NFPA for standard emergency evacuation signaling. Use them only for fire evacuation signaling and not for any other purpose.



### Notice

The prioritized tones used in each group are factory set and cannot be changed.

### Input Voltage and Sound Output Settings

The input voltage (12 VDC or 24 VDC) and the sound output (high dBA or standard dBA) are set with a jumper plug and a DIP switch.

## Certifications and approvals

Region	Certification	
USA	UL	UCST: Audible Signal Appliances, General Signal (UL464), ULSZ: Audible Signal Appliances (UL464)
	CSFM	see our website
Canada	ULC	ULSZC: Audible Signal Appliances and Accessories, Fire Alarm

## Installation/configuration notes

### Compatible Products

The following products are compatible with the AMT-12/24 appliances:

Category	Product ID	Product Description
Control Panels	D9412GV2 <sup>1</sup>	Control Panel
	D7412GV2 <sup>1</sup>	Control Panel
	D7212GV2 <sup>1</sup>	Control Panel
	D9412G <sup>1</sup>	Control Panel
	D7412G <sup>1</sup>	Control Panel
	D7212G <sup>1</sup>	Control Panel
	DS7400XiV4 <sup>1</sup>	Control Panel
	DS7400Xi <sup>1</sup>	Control Panel
	DS7200 Series <sup>1</sup>	Control Panels
	DS7080iP-32 <sup>1</sup>	Control Panel
	DS7060 Series <sup>1</sup>	Control Panels
	6000 Series <sup>1</sup>	Control Panels
	2000 Series <sup>1</sup>	Control Panels
	D7022 <sup>2</sup>	Conventional FACP
	D7024 <sup>3</sup>	Addressable FACP
	D7024	Conventional FACP
	D8024 <sup>4</sup>	Analog FACP
	D9124 <sup>4</sup>	Addressable FACP
	D10024A <sup>4</sup>	Analog FACP
	FPD-7024 <sup>3</sup>	Addressable FACP
FPD-7024	Conventional FACP	
FPA-1000	Analog Addressable FACPs	
Modules	SM-12/24-R	Synchronization module (red)
	DSM-12/24-R	Dual synchronization module (red)
	RSSP-121575W-FR	Fixed-candela retrofit strobe plate (12 V)

RSSP-241575W-FR Fixed-candela retrofit strobe plate (24 V)

RSSP-24MCW-FR Multi-candela retrofit strobe plate (24 V)

RSSP-24MCWH-FR High-candela retrofit strobe plate (24 V)

<sup>1</sup> For synchronization, use the SM or DSM modules with these control panels and set the horns and synchronization module for 12 VDC operation.

<sup>2</sup> The D7022 can be used in either 12 VDC or 24 VDC mode, but the horns and synchronization module must be set for the same operating voltage as the control panel.

<sup>3</sup> When used with a D7039 Multiplex Expansion Module, the FPD-7024 and D7024 become addressable fire alarm control panels (FACPs).

<sup>4</sup> For synchronization, use the SM or DSM modules with these control panels and set the horns and synchronization module for 24 VDC operation.



### Notice

The retrofit strobe plates are available in 12 V or 24 V models. Choose a model with the correct voltage for the control panel being used. Refer to *Use as Combination Appliance*.

### Mounting Considerations

Mount these horns on the indicated back boxes for the indicated applications:

	Conduit Applications	Surface Mounted	Semi-flush or Flush Mount
Double-gang			•
Four-inch square*		•	•
DBB Back Box*		•	•
IOB Back Box	•	•	

\* Use an ISP2 Surface Adapter between the appliance and the back box.

### Retrofit Applications

Where an oversize electrical box is already installed, the appliances can be installed with the RP-R Retrofit Plate that measures 8 in. (20.3 cm) high by 5.875 in. (14.9 cm) wide.

### Use as Combination Appliance

Where combination appliances are required, the AMT appliances can be used with the RSSP-121575W-FR (12 V, 15/75 cd), RSSP-241575W-FR (24 V, 15/75 cd), RSSP-24MCW-FR (24 V, 15 cd, 30 cd, 75 cd, or 110 cd), or RSSP-24MCWH-FR (24 V, 135 cd or 185 cd) Retrofit Strobe Plates that are designed to meet or exceed the latest requirements of NFPA 72, ANSI 117.0 and UL 1971. The multitone appliances and retrofit strobe plates are also compatible with the SBL2-R Retrofit Device Back Box.

### Outdoor or Severe Environment Applications

For an outdoor application or a severe environment (NEMA 3R) application, the appliance in combination with an IOB Indoor-Outdoor Back Box must be mounted on a flat wall using the supplied mounting ears such that the wall covers the entire rear surface of the back box. The back box must have its drain holes pointed toward the ground. The knockouts in the rear surface of the back box must remain intact. Use the supplied hole plugs to seal the unused mounting holes on the appliance's grill.

**Wiring**



**Notice**

The continuous horn and bell tones can be used on coded systems with a minimum on-time of 0.25 sec. Do not use the other tones of these horn units in coded or pulsed signaling circuits.

The input terminals accept wires with diameters between 18 AWG and 12 AWG (ISO 0.75 mm<sup>2</sup> and 4 mm<sup>2</sup>).

**Parts included**

Quant.	Component
1	Horn
1	Hardware pack
1	Literature pack

**Technical specifications**

**Electrical (12 VDC or FWR nominal)**

**Current (maximum):**

Continuous Horn:	High dBA: 210 mA (VDC), 230 mA (FWR) Standard dBA: 58 mA (VDC), 103 mA (FWR)
Bell:	High dBA: 117 mA (VDC), 150 mA (FWR) Standard dBA: 31 mA (VDC), 57 mA (FWR)
March Time Horn:	High dBA: 210 mA (VDC), 229 mA (FWR) Standard dBA: 59 mA (VDC), 91 mA (FWR)
Temporal Horn (Code 3):	High dBA: 210 mA (VDC), 241 mA (FWR) Standard dBA: 57 mA (VDC), 93 mA (FWR)
Temporal Tone (Code 3):	High dBA: 168 mA (VDC), 216 mA (FWR) Standard dBA: 62 mA (VDC), 100 mA (FWR)
Slow Whoop	High dBA: 182 mA (VDC), 212 mA (FWR) Standard dBA: 56 mA (VDC), 110 mA (FWR)
Siren	High dBA: 177 mA (VDC), 197 mA (FWR) Standard dBA: 55 mA (VDC), 107 mA (FWR)
Hi-Lo	High dBA: 131 mA (VDC), 186 mA (FWR) Standard dBA: 28 mA (VDC), 88 mA (FWR)
Vibrating Chime	High dBA: 90 mA (VDC), 108 mA (FWR) Standard dBA: 28 mA (VDC), 42 mA (FWR)

**Electrical (24 VDC or FWR nominal)**

**Current (maximum) VDC:**

Continuous Horn:	High dBA: 108 mA (VDC), 92 mA (FWR) Standard dBA: 43 mA (VDC), 50 mA (FWR)
Bell:	High dBA: 57 mA (VDC), 40 mA (FWR) Standard dBA: 26 mA (VDC), 28 mA (FWR)
March Time Horn:	High dBA: 108 mA (VDC), 92 mA (FWR) Standard dBA: 35 mA (VDC), 50 mA (FWR)
Temporal Horn (Code 3):	High dBA: 108 mA (VDC), 92 mA (FWR) Standard dBA: 43 mA (VDC), 50 mA (FWR)
Temporal Tone (Code 3):	High dBA: 60 mA (VDC), 51 mA (FWR) Standard dBA: 30 mA (VDC), 31 mA (FWR)
Slow Whoop	High dBA: 112 mA (VDC), 92 mA (FWR) Standard dBA: 44 mA (VDC), 50 mA (FWR)
Siren	High dBA: 102 mA (VDC), 78 mA (FWR) Standard dBA: 38 mA (VDC), 43 mA (FWR)
Hi-Lo	High dBA: 64 mA (VDC), 49 mA (FWR) Standard dBA: 30 mA (VDC), 34 mA (FWR)
Vibrating Chime	High dBA: 41 mA (VDC), 44 mA (FWR) Standard dBA: 20 mA (VDC), 29 mA (FWR)

**Environmental**

Relative Humidity:	Up to 98 ± 2%, non-condensing
Temperature (Operating):	-31°F to +150°F (-35°C to +66°C)

**Mechanical**

Material:	Molded plastic enclosure
-----------	--------------------------

**Sound Output Ratings (Reverberant dBA at 10 ft [3 m])**

Continuous Horn:	High dBA: 92 dBA Standard dBA: 86 dBA
Bell:	High dBA: 84 dBA Standard dBA: 78 dBA
March Time Horn:	High dBA: 88 dBA Standard dBA: 82 dBA
Temporal (Code 3) Horn:	High dBA: 88 dBA Standard dBA: 81 dBA
Temporal (Code 3) Tone:	High dBA: 84 dBA Standard dBA: 78 dBA
Slow Whoop	High dBA: 88 dBA Standard dBA: 83 dBA
Siren	High dBA: 89 dBA Standard dBA: 83 dBA
Hi-Lo	High dBA: 86 dBA Standard dBA: 81 dBA
Vibrating Chime	High dBA: 78 dBA Standard dBA: 71 dBA

**Notice**

The sound output for the Temporal (Code 3) mode is rated lower than in Continuous mode because the time that the horn is off is averaged into the sound output rating. When the horn produces a tone in Temporal mode, its sound pressure is the same as the Continuous mode.

**Ordering information****AMT-12/24-R Multitone Electronic Appliance (red)**

Red multitone electronic appliance for use in suppression releasing systems, combination security and emergency evacuation systems, and high risk installations.

Order number **AMT-12/24-R**

**Accessories****DBB-R Steel Back Box (red)**

8.6 cm (3.375 in.) square, 5.6 cm (2.1875 in.) deep  
Order number **DBB-R**

**IOB-R Indoor or Outdoor Back Box (red)**

13.3 cm (5.25 in.) square, 6.7 cm (2.625 in.) deep  
Order number **IOB-R**

**ISP2-R Surface Adapter (red)**

13.3 cm (5.25 in.) square, 3 cm (1.1875 in.) deep  
Order number **ISP2-R**

**ISP2-W Surface Adapter (white)**

13.3 cm (5.25 in.) square, 3 cm (1.1875 in.) deep  
Order number **ISP2-W**

**RP-R Retrofit Plate (red)**

20.3 cm (8 in.) high, 14.9 cm (5.875 in.) wide.

**Not Available.**

Order number **RP-R**

**SBB-R Surface-mount Back Box (red)**

14 cm (5.5 in.) x 14.2 cm (5.6 in.) x 9.1 cm (3.6 in.)  
Order number **SBB-R**

**SBB-W Surface-mount Back Box (white)**

14 cm (5.5 in.) x 14.2 cm (5.6 in.) x 9.1 cm (3.6 in.)  
Order number **SBB-W**

**SFP-R Semi-flush Plate (red)**

15.2 cm (6 in.) square by 0.8 cm (0.3125 in.) thick  
Order number **SFP-R**

**Represented by:****Americas:**

Bosch Security Systems, Inc.  
130 Perinton Parkway  
Fairport, New York, 14450, USA  
Phone: +1 800 289 0096  
Fax: +1 585 223 9180  
security.sales@us.bosch.com  
www.boschsecurity.us

**Europe, Middle East, Africa:**

Bosch Security Systems B.V.  
P.O. Box 80002  
5617 BA Eindhoven, The Netherlands  
Phone: + 31 40 2577 284  
Fax: +31 40 2577 330  
emea.securitysystems@bosch.com  
www.boschsecurity.com

**Asia-Pacific:**

Robert Bosch (SEA) Pte Ltd, Security Systems  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6571 2808  
Fax: +65 6571 2699  
apr.securitysystems@bosch.com  
www.boschsecurity.asia

**China:**

Bosch (Shanghai) Security Systems Ltd.  
201 Building, No. 333 Fuquan Road  
North IBP  
Changning District, Shanghai  
200335 China  
Phone +86 21 22181111  
Fax: +86 21 22182398  
www.boschsecurity.com.cn

**America Latina:**

Robert Bosch Ltda Security Systems Division  
Via Anhanguera, Km 98  
CEP 13065-900  
Campinas, Sao Paulo, Brazil  
Phone: +55 19 2103 2860  
Fax: +55 19 2103 2862  
latam.boschsecurity@bosch.com  
www.boschsecurity.com