SWM Series Mount

WALL MOUNT, SPECTRA®, DF5, AND SARIX™ ID AND IE SERIES PENDANT DOMES

Product Features

- For Use with Pelco Pendant Domes (Spectra[®], DF5, and Sarix[™] ID and IE Series) that Require a 1.5-inch NPT Pipe Thread for Installation
- Low Cost
- Constructed of Cast Aluminum
- · Cable Feedthrough Features
- Supports up to 10 lb (4.5 kg)
- Easy to Install, Using a Mounting Plate and Standard Tools
- Mounting Hardware is Concealed Within the SWM, Providing a Very Attractive Appearance
- Mounts Directly to a Vertical Load-Bearing Surface for Wall Mount Applications
- Can be used with the SWM-PA Series Pole Adapter or SWM-CA Series Corner Adapter
- For Indoor or Outdoor Applications

The **SWM Series** indoor/outdoor wall mounts are designed primarily for use with Pelco pendant domes including Spectra[®], DF5, DF8, and Sarix[™] ID and IE Series. They can also be used with other pendant domes that require a 1.5-inch NPT pipe thread for installation. Its unique design conceals the mounting bolts inside the mount, providing a clean and aesthetically pleasing appearance. It is easy to install and requires no special tools. A gasket is affixed to the base to protect the interior from moisture.

A feedthrough opening in the mounting surface allows for easy routing of video and power cables. Because of its compact size, the mount is not suitable for use with conduit fittings. A 1.5-inch NPT pipe thread is provided in the mount to attach the pendant dome.

For Sarix installations, the **SWM Series** wall mounts require a Sarix pendant mount adapter: the ID-P is required for Sarix ID Series domes, and the IE-P is required for Sarix IE Series domes.

Accessories for the wall mount include the **SWM-PA Series** pole adapter and the **SWM-CA Series** corner adapter. The corner adapter allows the wall mount to be attached to the corner of a building. The **SWM-CA24** corner adapter includes a 100 VA transformer that converts 120 or 230 VAC input to 24 VAC output. When installed with Sarix IE Series domes, the power from the **SWM-CA24** mount is used for the dome heater.

The wall mount and adapters are constructed of aluminum with a polyester powder coat finish. The wall mount is available in gray, light gray, black, and white. The pole adapter is available in gray, black, and white. The corner adapter is available in gray and white.






SWM-PA-GY POLE ADAPTER



SWM-CA CORNER ADAPTER



SWM-GY WALL MOUNT AND SWM-CA CORNER ADAPTER SHOWN WITH DF5-PG-EO



SWM-GY, SWM-BK, SWM-SR, SWM-WT NOTE: VALUES IN PARENTHESES ARE CENTIMETERS; ALL OTHERS ARE INCHES.



TECHNICAL SPECIFICATIONS

MODELS

SWM-GY	Wall mount with cable feedthrough; gray
OVVIVI G I	

finish

SWM-BK Same as SWM-GY except black finish SWM-SR Same as SWM-GY except light gray finish SWM-WT Same as SWM-GY except white finish*

*SWM mounts require the ID-P adapter for Sarix™ ID Series domes: the IE-P adapter is required for use with Sarix IE Series domes.

RELATED PRODUCTS

SWM-CA Corner adapter; gray finish

SWM-CAWT Same as SWM-CA except white finish Same as SWM-CA except includes internal SWM-CA24

transformer to convert 120 or 230 VAC input

to 24 VAC

SWM-PA-GY Pole adapter with stainless steel hardware;

gray finish

SWM-PA-BK Same as SWM-PA-GY except black finish SWM-PAWT Same as SWM-PA-GY except white finish

ELECTRICAL (SWM-CA24 ONLY)

Input Power 120/230 VAC, 50/60 Hz switchable **Output Power** 24 VAC (100 VA transformer)

Circuit Protection One 1.6 A, 120 VAC fast-acting fuse or one

500 mA, 230 VAC slow-blow fuse

GENERAL

Mounting Method

Wall Mount Mount is secured by a set screw to a

mounting plate that is attached to the mounting surface with two fasteners (not supplied) up to 0.25-inch (M6) diameter.

Corner Adapter Adapter is attached to a vertical load-bearing surface with two 0.375-inch (M8) diameter

stainless steel bolts of appropriate length (not supplied). Includes hardware to attach

SWM mount.

Pole Adapter Adapter is attached to a pole with two

> stainless steel straps (supplied). Straps fit 4 to 8-inch (10.16 to 20.32 cm) diameter pole. Includes hardware to attach SWM mount.

Cable Entry Cable feedthrough holes in mount adapters

Maximum Load 10 lb (4.5 kg) Environment Indoor/outdoor

Operating Temperature

(SWM-CA24 only) -50° to 120°F (-46° to 49°C)

Effective Projected Area (EPA) SWM-GY, SWM-BK,

SWM-SR, SWM-WT ~12 square inches

Construction

Wall Mount Cast aluminum Adapters Aluminum

Finish

SWM-GY, SWM-CA,

SWM-CA24,

SWM-PA-GY Gray polyester powder coat

SWM-BK,

SWM-PA-BK Black polyester powder coat Light gray polyester powder coat SWM-SR


SWM-WT, SWM-PAWT,


SWM-CAWT White polyester powder coat


Pelco, Inc. Worldwide Headquarters:

3500 Pelco Way, Clovis, California 93612-5699 USA USA & Canada Tel: (800) 289-9100 • FAX: (800) 289-9150 International Tel: +1 (559) 292-1981 • FAX: +1 (559) 348-1120

www.pelco.com







NOTE: VALUES IN PARENTHESES ARE CENTIMETERS; ALL OTHERS ARE INCHES.

Pelco, the Pelco logo, and other trademarks associated with Pelco products referred to in this publication are trademarks of Pelco, Inc. or its affiliates, All other product names and services are the property of their respective companies. Product specifications and availability are subject to change without notice. Copyright 2010, Pelco, Inc. All rights reserved.