
# HD-TVI 4MP IR Outdoor Mini Turret Camera Wall/Ceiling Mount, UTC, Multi-Format (TVI, AHD, CVI, CVBS) HT471TG – Grey, 2.9mm HT471TW – White, 2.9mm



200 New Highway, Amityville, NY 11701 800-645-5516 / www.specotech.com

#### **DIMENSIONS**



#### **FEATURES**

- Quad / Full HD resolution over coax
- Supports 4MP @ 30fps & 15fps (default), 2MP@30fps
- Multi-format HD (TVI default, CVI, AHD, CVBS)
- True day/night operation mechanical IR cut filter
- · Compact size only 2.36" in diameter
- 12 IR LEDs (IR range 35')
- Weather (IP66 compliant) / Vandal resistant operation
- 3-axis for wall and ceiling mounting
- Full OSD operation & Video format change through UT

#### C or Joystick built-in Cable


- · Signal distance up to 1600 feet\*
- 12VDC required
- 5 year warranty

#### **SPECIFICATIONS**

Image Sensor
1920x1080 @ 30fps
Video Output
Electronic Shutter Auto / Manual (1/30 – 1/30,000 sec.)
Day / Night Auto / Color / BW / External
Power 12VDC (power supply not included)
Power Consumption 12VDC, 300mA max.
Operating Temperature4° F – 122° F
Unit Dimensions
Unit Weight 10 oz.
Certifications FCC, RoHS
Signal Distance Up to 1600 feet
(depending on coax quality)*

#### **OSD MENU TREE**

(through UTC or Joystick built-in cable)



## **HD-TVI 4MP IR Outdoor Mini Turret Camera** Wall/Ceiling Mount, UTC, Multi-Format (TVI, AHD, CVI, CVBS) HT471TG - Grey, 2.9mm HT471TW - White, 2.9mm



200 New Highway, Amityville, NY 11701 800-645-5516 / www.specotech.com

#### 1) AE

BRIGHTNESS: Adjust Brightness of the lens (1~20)

EXPOSURE: GLOBE / CENTER / BLC / FLC

#### 2) WB

ATW: Auto Tracking White Balance.

- Use this mode when the color temp. is between 1,800~10,000K

#### MANUAL

- To fine-tune White Balance manually. Set White balance first by using ATW mode before Manual mode. After that, if there is still a white balance issue, switch to manual mode and have a fine-tune. Manual mode allows you to increase or decrease the red or blue factor.

#### 3) DAY / NIGHT

AUTO: No Use for IR cameras. **COLOR**: Display always color picture B/W: Display always B/W picture

**EXT**: Automatic D/N switching by using external signals.

#### 4) IMAGE ENHANCE

CONTRAST (1~50)

SHARPNESS: Adjusts sharpness level. Increasing this value, the

picture outline becomes stronger and clear. (1~20)

COLOR GAIN: Sets the desired Color Gain value (1~31)

DNR: To reduce the background noise in a low luminance

environment with 2D system.

**DNR**: To Change the video direction horizontally

D-WDR: (Digital Wide Dynamic Range): On / Auto / Off

- To distinguish an object in both bright and dare

areas.

5) VIDEO OUT: To change Video format (TVI/CVI/AHD/CVBS) To change frame rate (15/25/30)

6) LANGUAGE: 5 International OSD languages are supported.

7) RESET: to get all values as factory default values

8) SAVE-EXIT: to save current setting values and exit Main Menu

9) EXIT

## **speco** technologies

### LIMITED WARRANTY - VIDEO PRODUCTS I THIS TVARRANTY IS VALID ONLY ON PRODUCTS PURCHASED AND USED IN THE UNITED STATES OF AMERICA AND CANADA. THIS WARRANTY APPLIES ONLY TO THE ORIGINAL USER.

SUBJECT TO CONDITIONS AND EXCLUSIONS FOUND BELOW, THIS PRODUCT IS WARRANTED AGAINST MANUFACTURING DEFECTS IN MATERIAL AND WORKMANSHIP FOR THE FOLLOWING PERIOD FOR PARTS AND LABOR:

PECO TECHNOLOGIES CAMERAS 5 YEARS	DVRs5 YEARS
PECO TECHNOLOGIES IP CAMERAS 5 YEARS	NVRs5 YEARS
PECO PTZ1 YEAR	BALANCE OF
PECO TECHNOLOGIES MONITORS 1 YEAR	SPECO TECHNOLOGIES LINE1 YEAR
LEDG 00 DAVO	

SPECO TECHNOLOGIES WILL REPAIR OR REPLACE (AT OUR DISCRETION) ANY PARTS FOUND TO BE DEFECTIVE FOR THE WARRANTY PERIOD SPECIFIED. WE WILL PROVIDE A REPLACEMENT FOR ANY DEFECTIVE PART.

- YOU MUST OBTAIN A RETURN AUTHORIZATION (RA) NUMBER FOR ANY MERCHANDISE BEING RETURNED TO SPECO TECHNOLOGIES, WHETHER FOR RETURN/EXCHANGE OR REPAIR, WHETHER IN OR OUT OF WARRANTY.
- 2. THIS WARRANTY WILL BE HONORED ONLY UPON PRESENTATION OF THE ORIGINAL DATED BILL OF SALE OR SALES SLIP.
- TRANSPORTATION OF THE PRODUCT TO OUR SERVICE DEPARTMENT IS THE RESPONSIBILITY OF THE USER. REPAIRED OR REPLACED PRODUCT WILL BE RETURNED PREPAID DURING THE WARRANTY PERIOD.
- PRODUCT WILL BE RELIVINED YREA/IND DURING THE WARRANTY PERIOD.

  4, SPECO TECHNOLOGIES DOES NOTA JITHORIZE ANY INTERNET OR MAIL ORDER PRODUCT SALES. IF A SPECO TECHNOLOGIES PRODUCT IS PURCHASED FROM AN UNAUTHORIZED DISTRIBUTOR OR OTHER SOURCE. INCLUDING RETAILERS, MAIL ORDER SELLERS, IT AND ONLINE SELLERS, IT WILL NOT BE HONORED OR SERVICED INDER THE EXISTING SPECO TECHNOLOGIES WARRANTY POLICY ANY SPECO TECHNOLOGIES PRODUCT PURCHASED FROM THESE ONLINE MERCHANTS WILL VOID THE APPLICABLE WARRANTY AND IS INELIGIBLE FOR TECHNICAL SUPPORT, IF YOU HAVE QUESTIONS ABOUT A RESELLER, PLEASE CONTACT SPECO TECHNOLOGIES AT 1-800-445-5516 FOR A LIST OF UNAUTHORIZED DEALERS, WIST: www.specoden.com/unauthorized.

- THIS WARRANTY SHALL NOT COVER ADJUSTMENT OF CUSTOMER OPERATED CONTROLS AS EXPLAINED IN THE APPROPRIATE MODEL'S INSTRUCTION MANUAL OR PRODUCTS WHICH HAVE BEEN ALTERED, ABUSED, OR HAVE MISSING OR ALTERED SERIAL NUMBERS.
- 2. THIS WARRANTY SHALL NOT APPLY TO UNCRATING, SETUP, INSTALLATION, OR THE REMOVAL AND REINSTALLATION OF PRODUCTS
  AFTER REPAIR.
- THIS WARRANTY SHALL NOT APPLY TO REPAIRS OR REPLACEMENTS NECESSITATED BY ANY CAUSE BEYOND THE RESULT OF MANUFACTURE INCLUDING, BUT NOT LIMITED TO, ANY MALFUNCTION, DEFECTS OR FAILURE CAUSED BY OR RESULTING FROM INVALITHORIZED SERVICE OR PARTS, IMPROPER MAINTENANCE, MODIFICATION OR REPAIR BY THE USER, BAUSE, MISUSE, NEGLECT, ACCIDENT, FIRE, FLOOD, OR OTHER ACTS OF NATURE, INCORRECT LINE VOLTAGE, DAMAGE OR INVAGE BURNS TO TELEVISION PICTURE TUBES CAUSED BY OR ATTRIBUTABLE TO THE USE OF ANY ACCESSORY, ELECTRONICS GAME OR DEVICE, OR DAMAGE CAUSED TO IMAGE PICKUP DEVICES BY EXCESSIVE LIGHT.

THE FOREGOING IS IN LIEU OF ALL OTHER EXPRESSED WARRANTIES AND WE DO NOT AUTHORIZE ANY PARTY TO ASSUME FOR US ANY OTHER OBLIGATION OR LIABILITY. IN NO EVENT SHALL WE BE LIABLE FOR INCIDENTAL OR CONSEQUENTIAL DAMAGES ARISING FROM

THE USE OF THIS PRODUCT, OR FOR ANY DELAY IN THE USE OF THIS PRODUCT DUE TO CAUSES BEYOND OUR CONTROL. SOME STATES DO NOT ALLOW THE SECULISION OR LIMITATIONS OF HOW LONG AN IMPLIED WARRANTY LASTS ANDIOR DO NOT ALLOW THE SECULISION OR LIMITATION OF CONSEQUENTIAL DAMAGES MAY NOT APPLY TO YOU CONSEQUENTIAL DAMAGES MAY NOT APPLY TO YOU THIS WARRANTY GIVES YOU SPECIFIC LEGAL RIGHTS, YOU MAY HAVE OTHER RIGHTS WHICH VARY FROM STATE TO STATE.

NOTE: FOR YOUR PROTECTION IN THE EVENT OF THEFT OR LOSS OF THIS PRODUCT, PLEASE FILL IN THE INFORMATION REQUESTED BELOW AND DETAIN WITH YOUR SALES PECEIPT

MODEL NO.:	SERIAL NO.:
(LOCATED ON BACK OR BOTTOM OF UNIT)	
DATE OF PURCHASE:	
WHERE PURCHASED:	PURCHASE PRICE:

LWAYS USE DISCRETION WHEN INSTALLING VIDEO ANDIOR AUDIO SURVEILLANCE EQUIPMENT ESPECIALLY WHEN THERE VPECTATION OF PRIVACY, INQUIRE REGARDING FEDERAL, STATE ANDIOR LOCAL REGULATIONS APPLICABLE TO THE LOS STALLATION OF VIDEO ANDIOR AUDIO RECORDING OR SURVEILLANCE EQUIPMENT, PARTY CONSENT MAY BE REQUIRED

FOR MORE INFORMATION REGARDING SERVICE OR RETURN, CALL US TOLL FREE: 1-800-645-5516 IN METRO NY: 631-957-8700

Speco Technologies is constantly developing product improvements. We reserve the right to modify product design and specifications without notice and without incurring any obligation. Rev. 181101